

PRODUCT DETAILS

The Welling and Crossley P8750 is an AVR (automatic voltage regulated) generator with E-start. Supplied with transport kit (handles and wheels), this generator is Euro 5 emissions compliant. The generously sized fuel tank and economical motor allows longer run times. The WC-P8750 packs a lot of power in a compact footprint.

APPLICATIONS

- Work areas and construction sites to power lights, drills, saws, compressors, power tools etc.
- Whole home backup power
- Outdoor events for lights, sound systems etc
- Mobile businesses or market stalls to power appliances

FEATURES

- 2 x IP66 Outlets (single phase - 15 Amp)
- USB A and USB C outlets
- Recoil, Push-button electric, Wireless remote or 2 wire remote starting
- Steel frame with fold-out wheelbarrow style transport handle and large wheels
- 4-Stroke, air cooled, OHV engine
- Large 25L fuel tank
- Digital V/F/T Display (Volts, Frequency, Time)
- Low oil alarm, overload alarm, output indicator
- 2 year Welling and Crossley Warranty (battery excluded)



TECHNICAL DATA

ALTERNATOR RATING	8.75kVa with AVR
POWER FACTOR	1.0
MAX. AC OUTPUT	7000W
RATED AC OUTPUT	6800W
RATED MOTOR SPEED	3000rpm
RATED VOLTAGE	230/240V AC 1 Ph / 50Hz
ENGINE MODEL	WC-420: Euro 5 emissions compliant
ENGINE TYPE	4 stroke, OHV, air cooled. Transistor ignition
DISPLACEMENT	420cc

OIL	SAE10W-30
SPARK PLUG	Champion RN9YC
DECIBELS @ 7M DISTANCE	99 dBA
FUEL TYPE	Petrol – 91 octane unleaded.
FUEL TANK CAPACITY	25L
FUEL CONSUMPTION	Approx 1.48 L/Hr @ 1/4 load
PACKAGING (LXWXH)	710 x 535 x 590mm
DIMENSIONS	L: 700mm W: 600mm H: 660mm
WEIGHT	90kg