



## PRODUCT DETAILS

The Welling and Crossley P8000 is a 8 kVA portable capacitor type generator with E-start and 2 x 15 amp 230V outlets

Powered by a Honda petrol engine with electric start, it is the perfect size for almost everything,

The Honda Australia Approved GX390 engine is known and respected as a reliable workhorse, enabling this generator to run your power tools, compressor, a welder and much more.



## APPLICATIONS

- DIY workshops to power small to medium tools and lights
- Home back-up solution for essential appliances
- Outdoor events for lights, sound systems etc
- Mobile businesses or market stalls for powering small appliances

## FEATURES

- 2 x single phase 15 Amp outlets
- Recoil start, electric start
- Powerful & efficient: Honda Australia Approved Air cooled GX390 OHV 4-Stroke engine
- CDI Magneto Ignition
- Low oil level shutdown
- 2 year Welling and Crossley Warranty (battery excluded)

Total harmonic distortion 6 %



POWERED by **HONDA**



## TECHNICAL DATA

POWER RATING	8.0kVa
ALTERNATOR RATING	9.5kVa
RATED VOLTAGE	230/240 AC 1 Ph / 50Hz
RATED OUTPUT	Max 15 amp
RATED MOTOR SPEED	3000rpm
ENGINE MODEL	HONDA GX390
ENGINE TYPE	Single cylinder, 4 stroke, OHV air cooled petrol
DISPLACEMENT	389cc
OIL	1.1 litres SAE10W-40SE or SF

SPARK PLUG	NGK BPR6ES
NOISE LEVEL @ 7M	74 dBA
FUEL TYPE	Petrol – 91 octane unleaded.
FUEL TANK CAPACITY	6.1L
FUEL CONSUMPTION	Approx 2.58 L/Hr @ 80% load
OPERATION HOURS	2.36 hrs at 80% load
PACKAGING (L X W X H)	820 x 550 x 562mm
PRODUCT (L X W X H)	810 x 545 x 545mm
DRY WEIGHT	85kg