

EP8000HSRE-R/S

8 kVA Honda Powered Petrol Generator with Remote Start

This is the Perfect Back up Generator for unreliable solar power. The controller on the 2-wire remote start kit will start the generator from the closure of a remote contact. This allows you to start your generator without going out to it.

Specifications

Power Rating:	8 kVA
Alternator Rating:	9.5 kVA
Engine Model:	Honda GX390
Phase:	1 phase
Starting System:	Recoil/Electric
Fuel Tank Capacity (base mounted):	30 L
Noise Level @ 7m:	72 dBA
Approx. Fuel Consumption @ 80% Load:	2.58 L/Hr
Operation Hours @ 80% Load:	11.6 hrs
Fuel Type:	Petrol
Volts:	230 V
Outlets:	2 x 15Amp,
Dimensions:	780 x 570 x 570 mm
Weight:	120 kg



**Specifications are subject to change without notice*

OPTIONAL EXTRA P/N: 10-GN-N9-008

Attach the optional raised wheels & handles kit designed specifically for this model for easy maneuvering.

